

Matimo M-WM Series



Feature

- Noble designed with touching screen display ,optional Chinese / English language ;User could set the menu on the screen, very easy to operate .
- Built-in wireless microphone (optional),power amplifier , with professional karaoke effect .
- Dual karaoke chip makes frequency to be staggered and out of sync ,effectively prevent feedback , noise and other problems , to have a satiation and Natural voice
- Music , microphone , effect with starting up VOL setting and maximum VOL locked function .support One-key factory reset.
- High quality circuit board using micro control technology , The service life is longer than that of ordinary boards .
- Power amplifier support MP3 play , be available to listen any time the songs which already downloaded .
- Built-in 8 different optional scene mode .
- ARC audio signal pass back function.
- USB interface for toning software .
- High fidelity, large dynamic power amplifier ,super stability ,very full power .

Interface configuration

- ◆ HDMI2.0 , 4CH HDMI input and 1CH HDMI output .(optional accessory)
- ◆ Built-in 2 pcs high-end wireless microphone .(optional accessory)
- ◆ 1 digital optical input interface .
- ◆ 2 groups analog stereo input interface (VOD、DVD)
- ◆ 2CH external microphone input interface .
- ◆ Built-in 5.0 Bluetooth lossless player and MP3 played interface .
- ◆ USB interface for toning software .
- ◆ 2CH speaker output interface.

Technical parameters

2U	M-WM300	300W+300W (main channel) (8Ω , EIAJ)
	M-WM450	450W+450W (main channel) (8Ω , EIAJ)
	M-WM750	750W+750W (main channel) (8Ω , EIAJ)

weight: 15KG